

Compare copyA Hybrid Optical Network and a Method of Routing Data Packets
in a Hybrid Optical Network

5

CROSS-REFERENCE TO A RELATED APPLICATION

10 This application is a National Phase Patent Application of
International Patent Application Number PCT/EP2005/000932,
filed on January 26, 2005, which claims priority of European
Patent Application Number 04090028.4, filed on January 30,
2004.

DescriptionBACKGROUND

15

The invention regards a hybrid optical network with a single
channel optical ring network and a star network as well as a
method of routing data packets in a hybrid optical network.
More particularly, the invention regards an evolutionary
20 multichannel upgrade of an optical single channel packed
switched metropolitan area ring network and a method for
routing traffic in such upgraded network.

Document WO 99/37050 describes a communications system
25 including an optical network having a star topology in which
all network nodes are connected to a central hub. In
addition, a subset of the network nodes are connected via a
peripheral ring network. The central hub consists of multiple
WDM (wavelength division multiplex) routers. Traffic for
30 another node is directed over the star network or the
peripheral ring network depending on the shortest route.

Resilient Packet Ring IEEE 802.17 standard includes rules for
channel utilization, throughput efficiency, service
35 differentiation and resilience of optical single channel
packet switched ring metropolitan area networks (MANs). IEEE
802.17 regards a bidirectional dual-fiber ring network with

optical to electrical to optical signal conversion at each node. Each node is equipped with two fixed-tuned transmitters and two fixed-tuned receivers, one for each fiber ring.

- 5 There have been discussed ring networks that implement wavelength division multiplexing on the ring as an upgrade. However, such upgrade requires high investment costs as each node of the ring needs to be upgraded for WDM.

10 **SUMMARY**

There is a need ~~problem underlying the present invention is~~ to provide for a hybrid optical network that allows an evolutionary, cost sensitive upgrade of known single channel
15 optical ring network and a method of efficiently routing data packets in a hybrid optical network.

~~This problem is solved by a hybrid optical network with the features of claim 1 and a method of efficiently routing data
20 packets with the features of claim 16. Preferred and advantageous embodiments are identified in the subclaims.~~

Accordingly, ~~i~~In one embodiment a first aspect of the present invention there is provided a single channel optical ring
25 network that is upgraded by a star subnetwork. The star subnetwork comprises nodes which are formed by a a subset of the ring nodes of the ring network, i.e., only some of the ring nodes are also nodes of the star subnetwork. The star subnetwork additionally comprises a central wavelength router
30 having a plurality of input ports and a plurality of output ports and a plurality of combiners each having a plurality of input ports and one output port, the output ports of the combiners being connected to the input ports of the central wavelength router. Each node of the subset includes a tunable
35 transmitter and a tunable receiver to communicate optical data packets over the star subnetwork. The tunable transmitters are each connected to an input port of one of

the combiners. Optical data packets routed between two ring nodes of the subset over the star subnetwork are assigned a specific wavelength that determines the routing of the data packets through the central wavelength router.

5

One embodiment of ~~T~~the present invention is based on the idea to improve a single channel optical ring network, in which all ring nodes are connected by the ring, with a star subnetwork, to which only some of the ring nodes additionally
10 belong. This allows for an evolutionary upgrade of the network. Investment costs in the star subnetwork depend on the number of nodes that are added to the star subnetwork. To upgrade a node, only a transmitter and a receiver need to be added to the node. In addition, the use of combiners to which
15 the nodes of the star subnetwork are connected additionally reduces the number of input ports and output ports of the central wavelength router. This way, the number of costs for the central wavelength router is considerably reduced as such costs are proportional to the number of ports.

20

Also, the combiners serve as concentrators of network nodes and allow to reduce the amount of optical fibers required in the star subnetwork as well as the costs for installing such fibers. Using combiners, it is not necessary to connect each
25 node of the star subnetwork with a port of the central wavelength router. Furthermore, in case optical amplifiers are arranged between each combiner and the central wavelength router, such amplifiers are shared by a plurality of nodes of the star subnetwork, resulting in a reduced number of
30 required amplifiers.

The present invention applies wavelength division multiplexing only on the central wavelength router based star subnetwork, while leaving the ring network unchanged.

35

In a further advantage, the present invention allows for a large spatial reuse factor as the mean hop distance of the

network can be reduced by providing short-cuts over the star subnetwork. In particular, due to the short-cuts across the star subnetwork the hop distances on the ring network are decreased and the spatial reuse factor on the ring network is increased. Moreover, the central wavelength router as a wavelength routing device allows to spatially reuse all wavelengths at each port simultaneously.

It is pointed out that the terms "tunable transmitter" and "tunable receiver" as understood in the context of this invention denote both a transmitter or receiver that is tunable and an array of fixed-tuned transmitters or fixed-tuned receivers, in which "tuning" means to activate a transmitter or receiver of that array that emits or senses a desired wavelength. Also, a transmitter/receiver may consist of a combination of an array of fixed-tuned transmitters/receivers and one tunable transmitter/receiver. It is further pointed out that the tunable transmitter or tunable receiver can be combined in a tunable transceiver.

20

In a preferred embodiment of the invention, the central wavelength router is a single arrayed waveguide grating (AWG). There is only a single central router. The arrayed waveguide grating is a passive router. Due to its passive nature, the router is highly reliable.

25

In another preferred embodiment, the star subnetwork additionally comprises a plurality of wavelength independent splitters each having one input port and a plurality of output ports, the input ports of the splitters being connected to the output ports of the central wavelength router, the output ports of the splitters each being connected to a tunable receiver of one of the nodes of the subset. The use of splitters allows for multicasting. With multicasting, all network nodes connected to a splitter can receive a data packet which exits an output port of the central router. Accordingly, a data packet needs to be sent

30

35

less frequently to reach a plurality of nodes such that network resources are saved. Further, by using splitters (and combiners) it is possible to add more nodes to the star subnetwork having a given number of input ports and output
5 ports of the central wavelength router.

Preferably, the nodes of the subset are equally distributed among the ring nodes. This is advantageous to achieve a uniform traffic on the ring network and star subnetwork.

10

An optical amplifier may be arranged between the output port of a combiner and the corresponding input port of the central wavelength router and/or between an output port of the central wavelength router and the input port of the
15 corresponding splitter. Such optical amplifier compensates for fiber losses, splitting losses and insertion losses in the star subnetwork. The amplifier is, e.g., an Erbium doped fiber amplifier.

20 In a further embodiment of the present invention, each node of the subset comprises conversion means for optical to electrical to optical conversion of the optical signals. The tunable transmitter and the tunable receiver of a node perform electrical to optical and optical to electrical
25 signal conversion, respectively.

Preferably, each node of the subset comprises transit queues and station queues, the station queues comprising two receive queues and two transmit queues, one receive queue being
30 connected to the ring, one receive queue being connected to the tunable receiver, one transmit queue being connected to the ring and one transmit queue being connected to the tunable transmitter. Data packets stored in a transit queue are transferred to another ring node (store and forward).
35 Data packets stored in a station queue are received by the node or transmitted by the node and, if the node is not the

destination node, are sent across or received by the star subnetwork.

The hybrid network preferably further comprises protocol
5 means for routing optical data packets to be sent from a
given source ring node to a given destination ring node over
the shortest network path, including routing the data packets
over the single channel ring network and over the star
subnetwork. The shortest network path is determined, e.g., by
10 a network management system which can be a central management
system or a decentralized management system. The management
system, e.g., modifies look-up routing tables in the network
nodes. A media access control (MAC) protocol which belongs to
the data link layer (layer two of the OSI reference model) is
15 used to control access to the hybrid network. The MAC
protocol aims at maximizing the capacity of the network.

In a preferred embodiment, the hybrid network additionally
comprises: means for assigning a wavelength to data packets
20 being sent over the star subnetwork from a given source
subset node of the subset to a given destination subset node
of the subset, the wavelength determining the route of the
data packets through the star subnetwork; means for tuning
the tunable transmitter of the source subset node to the
25 assigned wavelength; and means for tuning the tunable
receiver of the destination subset node to the assigned
wavelength. This allows to send data from a given source
subset node of the star subnetwork to a given destination
subset node of the star subnetwork.

30 Said means for assigning a wavelength preferably comprise:
means for determining the shortest route for data packets
being sent from a given source ring node to a given
destination ring node; means for determining within the
35 shortest route a source subset node and a destination subset
node routing the data packets over the star subnetwork in a
short-cut; and means for determining a wavelength to route

the data packets from the source subset node to the destination subset node. The shortest route can be calculated by simply determining the shortest number of hops from one node to another for the data packets to get to their
5 destination. Using a short-cut over the star subnetwork counts as one hop. If data packets are routed over the star subnetwork, i.e., if a path across the subnetwork requires less hops than a path only over the optical ring, a wavelength is assigned to route the data packets across the
10 star subnetwork, i.e., from a source subset node to a destination subset node. The tunable transmitter and the tunable receiver of the respective subset node are tuned to this wavelength.

15 Preferably, the network further comprises means for putting the data packets received at the destination subset node on the single channel optical ring network in case the destination subset node is different from the destination node.

20

In a preferred embodiment, the single channel optical ring network is a bidirectional dual-fiber ring network. On one peripheral fiber ring, data packets are sent in a first direction, on another peripheral fiber ring, data packets are
25 sent in the opposite direction. There are provided electrical transit and station queues for either fiber ring. The use of a bidirectional ring is beneficial as data can be sent in both directions on the single channel optical ring. The spatial reuse factor is improved. However, the present
30 invention may just as well be implemented with a single channel unidirectional optical ring network.

In another preferred embodiment, a passive star coupler is arranged in parallel with the central wavelength router, each
35 node of the subset being coupled both to the central wavelength router and the passive star coupler. The central wavelength router routes data packets assigned to wavelengths

of a first waveband and the passive star coupler broadcasts data packets assigned to wavelengths of a second waveband. This embodiment allows for routing additional data over the passive star coupler of the star subnetwork.

5

In another embodiment ~~second aspect~~ of the present invention there is provided a method of routing data packets between a source ring node and a destination ring node of a hybrid optical network that comprises a peripheral optical ring
10 network with a plurality of ring nodes and a star network with a central wavelength router and a subset of the ring nodes, each node of the subset including means to communicate optical data packets over the star subnetwork. Preferably, the hybrid network as defined in claim 1 is used to carry out
15 the method.

The method is based on the idea to add a third kind of data stripping to the well known source stripping (the source node pulls data packets from the ring) and destination stripping
20 (the destination node pulls data packets from the ring) techniques. According to the inventive method, data are pulled from the ring by a node that is neither a source node nor a destination node. The node that pulls the data from the ring belongs to the star subnetwork and is termed source
25 subset node. The pulled data packets are transmitted over the star subnetwork to a destination subset node of the star subnetwork. The data packets are then sent from the destination subset node to the destination ring node again over the optical ring network if the destination ring node is
30 unequal to the destination subset node. The data packets are finally taken from the optical ring network by the destination ring node (destination stripping).

The inventive method will also be referred to as "proxy stripping" in contrast to the known methods of source
35 stripping and destination stripping.

Preferably, the source subset node and the destination subset node are nodes of the shortest route for data packets from the source ring node to the destination ring node over the hybrid network. Shortest path routing including short-cuts
5 over the star subnetwork is performed to increase the capacity of the network. The average number of hops (mean hop distance) is decreased.

However, it is pointed out that "proxy stripping" can be
10 implemented in shortest path routing or alternatively in any arbitrary routing policy. In shortest path routing, the ring nodes need to "know" which subset node is closest to the own location. This knowledge is contained, e.g., in a routing table in each ring node. Alternatively, in a transparent form
15 of proxy stripping, the ring nodes do not have any knowledge about the position of subset nodes on the ring. Proxy stripping is still executed, but the data packets may not take the shortest route from a ring node to a subset node. The advantage is that the ring nodes do not require
20 information about the position of the subset nodes. This is an advantage in particular if an existing ring network is upgraded with a star subnetwork in an evolutionary manner.

In a preferred embodiment, the optical data signals on the
25 optical ring network are converted to electrical data signals when taken from the ring. The electrical data signals are then converted to optical data signals of a specific wavelength that determines the routing of the data signals across the star subnetwork. In one embodiment, the optical
30 data signals are placed in a transmit queue when taken from the optical ring network and transmitted from the transmit queue to a tunable transmitter of the source subset node.

The method preferably additionally comprises the step of
35 regenerating the signal after conversion to an electrical signal. Such regeneration can be a 3R signal regeneration

(reamplifying, reshaping, retiming) well known to the skilled person.

5 In a further preferred embodiment, the source subset node transmits control data with node reservation information to the other nodes of the subset prior to transmitting the data over the star subnetwork. The node reservation information may comprise data about the source address of the source subset node, data about the destination address of the destination subset node and data about the length of the
10 corresponding data packet. The reservation protocol and control data may belong to the media access control (MAC) level of the network.

15 **BRIEF DESCRIPTION OF THE DRAWINGS**

The invention is explained in more detail below on the basis of an exemplary embodiment with reference to the figures, in which:

20

FigureIG. 1 shows a hybrid optical network including a single channel optical ring network and a star subnetwork having an arrayed waveguide grating as central wavelength router;

25

FigureFIG. 2 shows the main components of a ring node of the single channel optical ring network of figure FIG. 1;

30

FigureIG. 3 shows the main components of a ring node of the single channel optical ring network of figure FIG. 1 that also is a network node of the star subnetwork;

35

FigureIG. 4 shows in detail the arrangement of a plurality of combiners, a central arrayed waveguide grating

and a plurality of splitters in the star subnetwork
of ~~figure~~FIG. 1;

~~Figure~~FIG. 5 shows an alternative embodiment of a hybrid
optical network including a single channel optical
ring network and a star subnetwork, the star
subnetwork comprising both a central arrayed
waveguide grating and a central passive star
coupler; and

~~figure~~FIG. 6 shows the main components of a ring node of
the hybrid optical network of ~~figure~~FIG. 5 that is
also a network node of the star subnetwork.

DETAILED DESCRIPTION

~~Figure~~FIG. 1 depicts the network architecture of a hybrid
optical network. The hybrid optical network includes a bi-
directional dual-fiber ring consisting of two peripheral
fibers 11, 12 and a plurality of ring nodes 2. Each of the
ring nodes 2 is adapted to communicate single channel optical
data packets over the single channel ring network 1. To this
end, the ring nodes 2 each comprise two fixed-tuned
transceivers, one for each single channel fiber 11, 12, as
will be described in more detail below with respect to
~~figure~~FIG. 2.

The hybrid network additionally includes a star subnetwork 3.
The star subnetwork 3 comprises a plurality of subset nodes 4
which are a subset of the ring nodes 2 of the single channel
ring network 1. As will be explained in more detail with
respect to ~~figure~~FIG. 3, each subset node 4 of the star
subnetwork 3 comprises a tunable transmitter and a tunable
receiver to communicate optical data packets over the star
subnetwork 3.

The star subnetwork 3 additionally comprises a central wavelength router 5, which preferably is a single arrayed waveguide grating (AWG). The AWG 5 comprises D input ports and D output ports, $D \geq 2$. In addition, there are provided a plurality of wavelength insensitive combiners 6 and of wavelength insensitive splitters 7. The combiners 6 include S input ports and one output port, $S \geq 1$. The splitters 7 include one input port and S output ports. In the embodiment of figureFIG. 1, $S = D = 2$.

If $S = 1$, combiners would not be used. In such case, each node of the star subnetwork would be connected to a separate input port of the AWG 5.

The tunable transmitter of a given subset node 4 is connected to a combiner 6 input by using one fiber. Its tunable receiver is connected to the opposite splitter 7 output pair by using one fiber. The output port of the combiners 6 are connected to the input ports of the AWG 5. The input ports of the splitters 7 are connected to the output ports of the AWG. Accordingly, there are D combiners 6 and D splitters 7.

Optionally, between the combiners 6 and the AWG 5 as well as between the AWG 5 and the splitters 7 optical amplifiers 8 such as Erbium doped fiber amplifiers are placed to compensate for fiber losses, splitting losses and insertion losses.

FigureFIG. 2 diagrammatically depicts the main components of a ring node 2 of the single channel optical ring network 1. The ring node 2 comprises a fixed-tuned receiver FR 21, which converts the incoming optical data to electrical data. Depending on whether the received data are routed to another ring node 2 or are received at the given ring node 2, the data are sent to transit queues 23 or station queues 24.

The transit queues 23 comprise two queues, one for guaranteed class A traffic (primary transit queue - PTQ) 232 and one secondary transit queue STQ for class B (committed rate) and class C (best effort) traffic. If both queues PTQ 232 and STQ 231 are not full, highest priority is given to MAC traffic of the known MAC protocol. If there is no local control traffic, PTQ traffic is served always first. If PTQ 232 is empty, the local transmission queue (stage queue) is served until STQ 231 reaches a certain queue threshold. If STQ 231 reaches that threshold, STQ in-transit ring traffic is given priority over station traffic such that in-transit packets are not lost due to buffer overflow. This is in accordance with Resilient Packet Ring (RPR) IEEE 802.17 standard.

It is pointed out that this embodiment of the transit queues 23 is only exemplary. In an alternative embodiment, a single queue with a single FIFO queue is used.

The station queues 24 comprise one receive queue 241 and one transmit queue 242. The receive queue 241 comprises data packets that are received at the given ring node 2 for further processing. The transmit queue 242 comprises data packets that are put on the optical ring network at the ring node 2.

As the optical ring network is a single channel, i. e., a single wavelength network, the receiver 21 and the transmitter 22 are fixed-tuned receivers and transmitters, respectively. The transmitter 22 converts the electrical data to optical data and puts the optical data on the ring. In addition, signal regeneration such as 3R signal regeneration including reamplifying, reshaping and retiming may be carried out in the electrical part of the node 2.

FigureFIG. 3 diagrammatically depicts a subset node 4 which belongs both to the single channel optical ring network 1 and the star subnetwork 3. The subset node 4 comprises the

elements of a ring node 2 as described with respect to figureFIG. 2, such that reference is made to figureFIG. 2 in that respect. In addition, a tunable receiver 25 and a tunable transmitter 26 are provided. The tunable receiver 25
 5 is connected to the receive queues 241. The tunable transmitter 26 is connected to the transmit queues 242. By means of the tunable transmitter 26, optical data can be transmitted from the given subset node 4 across the star subnetwork 3. The tunable receiver 25 is used to detect
 10 optical signals received from the star subnetwork 3 and to convert them into electrical signals.

Preferrably, all queues are implemented as FIFO queues.

15 It is pointed out that each subset node 4 is equipped with two transit queues 23 and two station (receive and transmit) queues 24, one for each fiber ring of the bidirectional ring 1, and two additional station (receive and transmit) queues for the star subnetwork. However, only one set of PTQ and STQ
 20 queues 23 is shown in figureFIG. 3. The same is true for the ring nodes 2 of figureFIG. 2.

FigureFIG. 4 shows the network structure of the star subnetwork 3. The single central AWG 5 is a frequency-cyclic
 25 DxD arrayed waveguide grating with D input ports and D output ports, where $D \geq 2$.

The subset nodes 4 of the star subnetwork 3 each includes a tunable transmitter TT and a tunable receiver TR, as
 30 explained with respect to figureFIG. 3. The total number of subset nodes 4, and accordingly of tunable transmitters TT and tunable receivers TR is $S \times D$, with S being the number of input ports of the combiners 6-1, 6-2, ..., 6-D. S is also the number of output ports of the splitters 7-1, 7-2 ..., 7-
 35 D.

To the input ports of a first $S \times 1$ combiner 6-1 are connected S tunable transmitters TT_1, \dots, TT_S . To the input ports of a second combiner 6-2 are also connected S tunable transmitters TT , etc. Each combiner 6-1, 6-2, ..., 6-D collects data from
 5 S attached tunable transmitters TT and feeds them into one AWG input port.

The output ports of a first $1 \times S$ splitter 7-1 are connected to S tunable receivers TR_1, \dots, TR_S . The same is true for
 10 further splitters 7-2, ..., 7-D, each connected to an output port of the AWG 5. By using the splitters 7-1, 7-2, ..., 7-D, the AWG output port signals of a given output port are equally distributed to S attached tunable receivers TR by the wavelength-insensitive $1 \times S$ splitters. These wavelength-
 15 insensitive splitters also enable optical multicasting.

The wavelength $\lambda_1, \lambda_2, \dots, \lambda_D$ of the tunable transmitters TT and of the tunable receivers TR determines the route of data packets encoded by signals of that wavelength $\lambda_1, \lambda_2, \dots, \lambda_D$
 20 through the AWG 5 and, accordingly through the star subnetwork 3. The AWG 5 routes different wavelengths $\lambda_1, \lambda_2, \dots, \lambda_D$ from tunable transmitters $TT_1 \dots TT_S$ and combined at combiner 6-1 to different output ports of the AWG 5. The same is true for wavelengths applied to the AWG through the other
 25 combiners 6-2 ... 6-D. The AWG 5 routes wavelengths such that no collisions occur at the AWG output ports, i. e., each wavelength can be applied to all AWG input ports simultaneously. In other words, with a $D \times D$ AWG each wavelength can be spatially reused D times.

30 Additional wavelengths can be used if several free spectral ranges (FSR) of the AWG 5 are used. The free spectral range is also known as the demultiplexer periodicity. This periodicity is due to the fact that constructive interference
 35 at the output ports occurs for a number of wavelengths. One can also describe the free spectral range as the spectral

distance to the next diffraction order of the grating of the AWG.

Using R FSRs, $R \geq 1$, allows for R simultaneous transmissions
 5 between each AWG input port and output port pair. Thus, the total number of wavelength channels available for routing at each AWG port is D times R , where $R \geq 1$.

Accordingly, each transmitter TT and each receiver TR needs
 10 to be tunable over $R \times D$ contiguous wavelength channels in order to provide full connectivity in one single hop over the central router 5. Alternatively, a subset of the tunable transmitters TT and the tunable receivers TR are tunable over D contiguous wavelength channels only, with different tunable
 15 transmitters TT and tunable receivers TR being tunable over wavelengths of different free spectral ranges of the AWG 5. However, this way a restriction occurs regarding which subset nodes of the star subnetwork can communicate. If $R = 1$, it is sufficient that the transmitters and receivers are tunable
 20 over D contiguous wavelength channels in order to provide full connectivity in one single hop.

To route data packets from a first given subset node and its tunable transmitter TT to a second given subset node and its
 25 tunable receiver TR, a wavelength of the number of wavelengths $R \times D$ has to be determined and the respective tunable transmitter and tunable receiver have to be tuned to that wavelength. Once this is carried out, the route of the data packets through the AWG 5 and thus through the star
 30 subnetwork 3 is determined.

The wavelength channel access of the tunable transmitters and receivers is arbitrated by means of a reservation protocol with pretransmission coordination, as will be further
 35 described.

Referring again to figureFIG. 1, it is now discussed the transport of data packets between a given source ring node A and a given destination ring node B of the hybrid network. Both nodes A and B are ring nodes 2 only and not part of the
 5 star subnetwork 3.

The data packets to be sent from node A to node B are first put on the optical ring network 1 at the source ring node A. It is then determined a route for the data packets being sent
 10 from the source node A to the destination node B. Such determination is made, e. g., by a network management system and/or routing protocols. Preferably, the shortest path through the network from node A to node B is determined to keep a high network capacity for newly generated traffic.

15 The shortest route is the route that requires the lowest number of hops from one node to an adjacent hop on the way a packet takes from the source node A to the destination node B. In the example discussed in figureFIG. 1, it would take a
 20 data packet seven hops to travel to node B across the ring network and four hops to travel to the node B by taking the short cut between subset nodes 4 over the star subnetwork 3. Accordingly, the route across the star subnetwork 3 is the shortest route.

25 It is determined which source subset node 4 and destination subset node 4 of the subset are part of the shortest route. These subset nodes receive information to route data packets from source node A via the star subnetwork 3 to the
 30 destination subset node. To this end, e. g., the routing tables of the subset node 4 are updated accordingly by means of control packets.

The data packets sent from node A are then pulled from the
 35 optical ring 1 at the source subset node 4 closest to the source node A. The data are transmitted over the star subnetwork 3 to the destination subset node 4 closest to the

destination node B. To this end, optical-electrical-optical conversion of the data is carried out at the nodes and a specific wavelength is assigned to the data packets which are sent over the star subnetwork 3. The assigned wavelength
5 determines the route of the data packets through the star subnetwork 3. The tunable transmitter 26 and the tunable receiver 25 of the respective subset nodes 4 are tuned to that wavelength.

10 Once the data packets routed through the star subnetwork 3 are received at the destination ring node 4, the data packets are sent from the destination subset node 4 over the optical ring network 1 to the destination node B. The destination node B takes the data packets from the optical ring network 1
15 (destination stripping).

Once a data packet is safely received at the destination node B, an acknowledgement ACK control packet is sent to the source node A. This preferably is done over the ring network
20 1 only. The acknowledgement control packets as well as reservation control packets are implemented in the media access control (MAC) level of the network.

The invention introduces the novel concept of "proxy stripping", how the routing of data packets as described
25 above is termed.

With proxy stripping, other than with source stripping or destination stripping, a subset node (which may also be
30 termed ring-and-star homed node) which is neither a source node nor a destination node pulls incoming data from the ring network and sends them across the star subnetwork 3 in a single-hop short-cut over the AWG 5.

35 If the shortest route between a given source and destination node does not include the star subnetwork 3, then destination stripping without proxy stripping is used. For example, if in

figureFIG. 1 data are sent from a source node A to a destination node B', the shortest route would be that over the peripheral ring network 1. In such case, proxy stripping would not be executed.

5

Using proxy stripping, and additional referring to figureFIG. 3, a subset node 4 takes the corresponding data packets from the ring and places the data packets in its star transmit queue 242. As mentioned above, a subset node 4 only pulls data packets from the ring, if the minimum hop distance between a given source node 2 and a given destination node 2 on the ring 1 is larger than the minimum hop distance between a given source node 2 and a given destination node 2 via short-cuts across the star subnetwork 3.

15

Packets in the star transmit queue 242 are sent by using a reservation protocol with pretransmission coordination. Prior to transmitting a data packet, the corresponding subset node 4 broadcasts a control packet on one of the fiber rings by means of source stripping or across a wavelength insensitive PSC (see Fig. 5). The control packet preferably consists of three fields: first, the source address of the proxy-stripping source subset node, second, the destination address of the destination subset node that is closest to the destination node and, third, the length of the corresponding data packet. Each subset node 4 receives the broadcast control packet and is thus able to acquire and maintain global knowledge of all subset nodes 4 reservation requests. Based on this global knowledge, all subset nodes 4 schedule the transmission and reception of the corresponding data packets over the star subnetwork 3 in a distributed fashion. For example, a deterministic first-come-first-served and first-fit scheduling algorithm is used.

35 The described hybrid network allows for an evolutionary WDM upgrade of an optical single channel ring network in that it builds into the single-channel node structure while leaving

the ring network unchanged. Only a subset of the ring nodes of the single channel ring network needs to be upgraded. Accordingly, nodes can be upgraded and connected to the star subnetwork via dark fibers one at the time in a pay-as-you-grow manner. The described hybrid network requires only one single router, which is sufficient to provide for single-hop interconnection among all subset nodes. The central wavelength router is highly reliable due to its passive nature.

In an alternative embodiment of the star subnetwork, the star subnetwork does not implement splitters 7. Instead, the exit ports of the AWG 5 are connected directly via fibers to tunable receivers of the subset nodes 4. Although multicasting is not possible in this embodiment, a point to point connection is still possible.

In a further alternative embodiment, the single channel optical ring network is a unidirectional ring network with one peripheral fiber only, such that data can be sent over the ring network in one direction only. By using a bidirectional network, the spatial reuse of bandwidth is increased. It is further possible to use a bidirectional single-fiber ring network.

~~Figure~~FIG. 5 shows a hybrid optical network that, in comparison with the hybrid optical network of ~~figure~~FIG. 1, additionally includes a passive star coupler (PSC) 15 which is located in parallel with the central AWG 5. In the following, only those features of the hybrid optical network are described which are in addition to the features of the hybrid optical network of ~~figure~~FIG. 1. The components discussed in ~~figure~~FIG. 1 are also present in the hybrid optical network of ~~figure~~FIG. 5.

The passive star coupler 15 has D input ports and D output ports, where $D \geq 2$. The passive star coupler 15 has thus the

same number of input ports and output ports as the central
 AWG 5. The passive star coupler 15 functions like a $D \times 1$
 combiner and a $1 \times D$ splitter interconnected in series.
 Accordingly, it collects wavelength channels from all D input
 5 ports and equally distributes them among all D output ports.
 Similar to the splitters 7, a given wavelength channel can be
 received at all D output ports. Similar to the combiners 6,
 to avoid channel collisions at the output ports, a given
 wavelength channel can be used only at one of the D input
 10 ports at any time.

The input ports of the passive star coupler 15 are each
 connected to a waveband partitioner 91. Each waveband
 partitioner 91 is located between the output port of a
 15 combiner 6 and an input port of the AWG 5 and the PSC 15. In
 case the signals are amplified by an optical amplifier 8, the
 waveband partitioner 91 is preferably arranged between such
 optical amplifier 8 and the AWG 5 and PSC 15.

20 The waveband partitioner 91 has one input port and two output
 ports. It partitions an incoming set of contiguous wavelength
 channels Λ into two wavebands (subbands Λ_{AWG} and Λ_{PSC}), where
 $\Lambda = \Lambda_{\text{AWG}} + \Lambda_{\text{PSC}}$. Each waveband Λ_{AWG} , Λ_{PSC} is routed through a
 different output port. One output port of the waveband
 25 partitioner 91 is connected to an input port of the AWG 5 and
 one output port of the waveband partitioner 91 is connected
 to one input port of the PSC 15.

In a symmetrical manner, there are also provided waveband
 30 departitioners 92. Each waveband departitioner 92 has two
 input ports and one output port, the input ports being
 connected to the AWG 5 and the PSC 15, respectively, and the
 output port being connected to the input port of a splitter 7
 or, if present, an optical amplifier 8 arranged between the
 35 waveband departitioner 92 and the splitter 7. The waveband
 departitioner 92 collects the two different wavebands Λ_{AWG}
 and Λ_{PSC} of contiguous wavelength channels from the two input

ports. The combined set of Λ wavelength channels is launched onto the common output port, where $\Lambda = \Lambda_{\text{AWG}} + \Lambda_{\text{PSC}}$.

The waveband Λ_{AWG} comprises $D \times R$ contiguous wavelength channels, i. e., $\Lambda_{\text{AWG}} = D \times R$. R denotes, as explained above, the number of used FSRs of the underlying AWG 5. The second waveband Λ_{PSC} comprises $1 + D \times S$ contiguous wavelength channels, i. e., $\Lambda_{\text{PSC}} = 1 + D \times S$. There is provided in waveband Λ_{PSC} one control channel with wavelength λ_c and $D \times S$ data channels, one for each subset node 4 of the star subnetwork. A set of Λ wavelength channels are combined by means of $S \times 1$ combiner 6 which collects individual wavelength channels from S subset nodes, where $S \geq 1$ as explained with respect to figureFIG. 1. The wavelength channels are split into two wavebands by waveband partitioner 91. The waveband departitioner 92 collects the two wavebands Λ_{AWG} and Λ_{PSC} from each pair of output ports of both AWG 5 and PSC 15. The combined set of wavelength channels is equally distributed among the S attached subset nodes by means of the $1 \times S$ splitter 7, where $S \geq 1$.

The addition of a passive star coupler 15 to the hybrid optical network requires a modified structure of the subset nodes 4, which are both part of the ring network 1 and the star subnetwork 3. Such modified structure of a subset node 4 is depicted in figureFIG. 6.

The subset node 4 of the hybrid network of figureFIG. 5 comprises the elements of a subset node as described with respect to figureFIG. 3, such that reference is made to figureFIG. 3 in that respect. In addition, there are provided a fixed tuned transmitter 27 for additionally transmitting control and data signals into the star subnetwork and two fixed-tuned receivers 28, 29 for additionally receiving signals from the star subnetwork.

The additional fixed-tuned transmitter 27 is tuned to a control wavelength channel λ_c of waveband Λ_{PSC} . As mentioned above, $\Lambda_{PSC} = 1 + D \times S$. The remaining $D \times S$ wavelength channels of the waveband Λ_{PSC} and all wavelength channels of waveband Λ_{AWG} are accessed for data transmission by the tunable transmitter 26 whose tuning range equals:

$$D \times S + \Lambda_{AWG} = D(S+R).$$

For reception of signals from the star subnetwork, additional fixed-tuned receiver 29 is tuned to the control wavelength channel λ_c of waveband Λ_{PSC} . In addition, further additional fixed-tuned receiver 28 is provided for data reception on the passive star coupler 15. The further fixed-tuned receiver 28 is operated at its own dedicated home channel λ_i which is one of the wavelength channels of Λ_{PSC} . Accordingly, each data wavelength channel of waveband Λ_{PSC} is dedicated to a different subset node 4 for signal reception. Consequently, data packets transmitted on PSC 15 data wavelength channels do not suffer from receiver collision. In this respect, it is noted that a receiver collision occurs when the receiver of the intended destination node is not tuned to the wavelength channel on which the data packet was sent by the corresponding source node.

In addition, on the wavelength channels of waveband Λ_{AWG} , data packets are received by the tunable receiver 25 as explained with respect to figureFIG.s 1 to 4.

It is pointed out that transit queues 231, 232 are depicted in figureFIG. 6 only for one single channel fiber of the bi-directional dual fiber ring which consists of two peripheral fibers 11, 12 each carrying one wavelength. Transit queues as well as one transmit and one receive queue are also provided for the other ring. In addition to these transit queues and station queues, each subset node has a separate transmit queue for each transmitter (either fixed-tuned or tunable) and a separate receive queue for each receiver (either fixed-

tuned or tunable). Accordingly, besides the four transit queues (two for either ring), each subset node has four transmit queues and five receive queues in total. Preferably, all queues are FIFO queues.

5

It will now be discussed the benefits of adding a passive star coupler 15 as explained with respect to ~~figure~~FIG.s 5 and 6 to the hybrid optical network of ~~figure~~FIG. 1.

10 First, the wavelength channel λ_c of fixed wavelength allows to broadcast control information to all other subset nodes 4. It is thus possible to send control data to all other subset nodes 4 over the star subnetwork 3, without occupying bandwidth on the ring network 1 and without bothering ring
15 nodes 2 which are not subset nodes with the routing of such control data. An example for such control data are control data which are used in a reservation protocol with pretransmission coordination, e.g., when informing the subset nodes 4 about reservation requests when sending data packets
20 over the AWG 5.

Also, using the wavelength channel λ_c , large amounts of data can be multicast to a plurality of receivers without using the ring network 1.

25

Second, the further $D \times S$ wavelength channels of waveband Λ_{PSC} can be used to send data over the PSC 15 to a specific destination node 4 which is part of the star subnetwork. To this end, a tunable transmitter 26 of a source subset node
30 will tune to a specific wavelength λ_i to which the fixed-tuned receiver 28 of one of the destination subset nodes is fixed-tuned. Although the data packets sent out from tunable transmitter 26 will be broadcast by the PSC 15 to all other subset nodes 4, only the one subset node with its fixed-tuned
35 receiver 28 tuned to wavelength λ_i will be able to detect these signals. Compared with the transmission of data over AWG 5, it is not required to perform wavelength tuning at the

destination node. The receiver of the intended destination is always tuned to its dedicated wavelength channel λ_i . However, an additional fixed-tuned receiver 28 is required at the subset node 4.

5

In supplementing the star subnetwork of ~~figure~~FIG. 1 with a passive star coupler 15, additional possibilities and flexibility in routing data packets to a destination node are provided.

10

It is pointed out that the novel concept of "proxy stripping" as explained with respect to ~~figure~~FIG.s 1 to 4 also applies to the hybrid optical network of ~~figure~~FIG. 5. Obviously, short cuts over the star subnetwork can be routed over the
15 AWG 5 or the PSC 15.

20

The invention is not restricted in its configuration to the exemplary embodiments presented above, which are to be understood as only given by way of example. A person skilled in the art recognizes the existence of numerous alternative variants for the embodiment, which, in spite of their departure from the exemplary embodiments described, make use of the teaching defined in the claims.

Claims

1. ~~A hybrid optical network comprising:~~

- ~~-a single channel optical ring network (1),~~
- 5 ~~-a plurality of ring nodes (2) of the single channel optical ring network (1), each of the ring nodes (2) being adapted to communicate single channel optical data packets over the single channel ring network (1),~~
- 10 ~~-a star subnetwork (3) comprising:~~
 - ~~▪ a central wavelength router (5) having a plurality of input ports and a plurality of output ports,~~
 - 15 ~~▪ a plurality of combiners (6) each having a plurality of input ports and one output port, the output ports of the combiners (6) being connected to the input ports of the central wavelength router (5),~~
 - 20 ~~▪ a subset of the ring nodes (4) of the ring network, each node (4) of the subset including a tunable transmitter (26) and a tunable receiver (25) to communicate optical data packets over the star subnetwork (3), the tunable transmitters (26) each being connected~~
 - 25 ~~to an input port of one of the combiners (6), wherein~~
 - ~~-optical data packets routed between two ring nodes (4) of the subset over the star subnetwork (3) are assigned a specific wavelength that determines the~~
 - 30 ~~routing of the data packets through the central wavelength router (5).~~

2. ~~The network according to claim 1, wherein the central wavelength router (5) is a single arrayed waveguide~~
35 ~~grating.~~

3. ~~The network according to claim 1 or 2, additionally comprising a plurality of wavelength independent splitters (7) each having one input port and a plurality of output ports, the input ports of the splitters (7) being connected to the output ports of the central wavelength router (5), the output ports of the splitters (7) each being connected to a tunable receiver (25) of one of the nodes (4) of the subset.~~
- 5
4. ~~The network according to any preceding claim, wherein the nodes (4) of the subset are equally distributed among the ring nodes (2).~~
- 10
5. ~~The network according to any preceding claim, wherein an optical amplifier (8) is arranged between the output port of a combiner (6) and the corresponding input port of the central wavelength router (5).~~
- 15
6. ~~The network according to any of claims 3 to 5, wherein an optical amplifier (8) is arranged between an output port of the central wavelength router (5) and the input port of the corresponding splitter (7).~~
- 20
7. ~~The network according to any preceding claim, wherein each node (4) of the subset comprises conversion means (21, 22) for optical to electrical to optical conversion of the signals, and wherein the tunable transmitter (26) and the tunable receiver (25) of a node (4) perform electrical to optical and optical to electrical signal conversion, respectively.~~
- 25
- 30
8. ~~The network according to claim 7, wherein each node (4) of the subset comprises transit queues (23) and station queues (24), the station queues (24) comprising receive queues (241) and transmit queues (242), one receive queue (241) being connected to the tunable receiver (25) and~~
- 35

~~one transmit queue (242) being connected to the tunable transmitter (26).~~

5 ~~9. The network according to any preceding claim, further comprising protocol means for routing optical data packets to be sent from a given source ring node (2, A) to a given destination ring node (2, B) over the shortest network path, including routing the data packets over the single channel ring network (1) and over the star subnetwork (3).~~

~~10. The network according to any preceding claim, additionally comprising:~~

15 ~~-means for assigning a wavelength to data packets being sent over the star subnetwork (3) from a given source subset node (4) of the subset to a given destination subset node (4) of the subset, the wavelength determining the route of the data packets through the star subnetwork (3),~~

20 ~~-means for tuning the tunable transmitter (26) of the source subset node (4) to the assigned wavelength, and~~

25 ~~-means for tuning the tunable receiver (25) of the destination subset node (4) to the assigned wavelength.~~

~~11. The network according to claim 10, wherein the means for assigning a wavelength comprise:~~

30 ~~-means for determining the shortest route for data packets being sent from a given source ring node (2, A) to a given destination ring node (2, B),~~

35 ~~-means for determining within the shortest route a source subset node (4) and a destination subset node (4) routing the data packets over the star subnetwork (3) in a short-cut,~~

~~means for determining a wavelength to route the data packets from the source subset node (4) to the destination subset node (4).~~

5 ~~12.The network according to claim 10 or 11, further comprising means for putting the data packets received at the destination subset node (4) on the single channel optical ring network (1) in case the destination subset node (4) is different from the destination node (2, B).~~

10

~~13.The network according to any preceding claim, wherein the single channel optical ring network (1) is a bidirectional dual-fiber ring network or a bidirectional single-fiber ring network.~~

15

~~14.The network according to any preceding claim, wherein the hybrid optical network is a packet switched metropolitan area network.~~

20 ~~15.The network according to any preceding claim, wherein a passive star coupler (15) is arranged in parallel with the central wavelength router (5), each node (4) of the subset being coupled both to the central wavelength router (5) and the passive star coupler (15), and with~~
25 ~~the central wavelength router (5) routing data packets assigned to wavelengths of a first waveband and the passive star coupler (15) routing data packets assigned to wavelengths of a second waveband.~~

30 ~~16.A method of routing data packets between a source ring node (2, A) and a destination ring node (2, B) of a hybrid optical network that comprises a peripheral optical ring network (1) with a plurality of ring nodes (2) and a star network (3) with a central wavelength~~
35 ~~router (5) and a subset of the ring nodes (2), each node (4) of the subset including means (25, 26) to communicate~~

~~optical data packets over the star subnetwork (3), the method comprising:~~

- ~~-putting data packets to be transmitted on the optical ring network (1) at the source ring node (2, A),~~
- 5 ~~-determining a source subset node (4) and a destination subset node (4) of the subset which are part of a route for data packets being sent from the source ring node (2, A) to the destination ring node (2, B),~~
- 10 ~~-pulling incoming source ring node data packets from the optical ring network (1) at the source subset node (4),~~
- ~~-transmitting the pulled data packets over the star subnetwork (3) to the destination subset node (4),~~
- 15 ~~-sending the data packets from the destination subset node (4) to the destination ring node (2, B) over the optical ring network (1) if the destination ring node (2, B) is unequal to the destination subset node (4), and~~
- 20 ~~-taking the data packets from the optical ring network (1) at the destination ring node (2, B).~~

17. ~~The method of claim 16, wherein the source subset node (4) and the destination subset node (4) are nodes of the shortest route for data packets from the source ring node (2, A) to the destination ring node (2, B) over the hybrid network.~~

18. ~~The method of claim 16 or 17, wherein the optical ring network (1) is a single channel optical ring network, the optical data packets pulled from the single channel optical ring network (1) being converted in the source subset node (4) to an optical wavelength that allows routing of the data packets to the destination subset node (4) over the star subnetwork (3).~~

19. ~~The method of claim 18, wherein the optical data signals on the optical ring network (1) are converted to electrical data signals when taken from the ring, and wherein the electrical data signals are converted to optical data signals of a specific wavelength that determines the routing of the data signals across the star subnetwork (3).~~
20. ~~The method of claim 19, wherein the optical data signals are placed in a transmit queue (242) when taken from the optical ring network (1) and transmitted from the transmit queue (242) to a tunable transmitter (26) of the source subset node (4).~~
21. ~~The method of claim 19 or 20, additionally comprising the step of regenerating the signal after conversion to an electrical signal.~~
22. ~~The method of any of claims 16 to 21, additionally comprising the step of the source subset node (4) transmitting control data with node reservation information to the other nodes (4) of the subset prior to transmitting the data packets over the star subnetwork (4).~~
23. ~~The method of claim 22, wherein the node reservation information comprises data about the source address of the source subset node (4), data about the destination address of the destination subset node (4) and data about the length of the corresponding data packet.~~

24. A hybrid optical network comprising:

- a single channel optical ring network—(1),
- a plurality of ring nodes (2)—of the single channel optical ring network—(1), each of the ring nodes (2) being adapted to communicate single channel optical data packets over the single channel ring network (1),
- a star subnetwork (3)—comprising:
 - a central wavelength router (5)—having a plurality of input ports and a plurality of output ports,
 - a plurality of combiners (6)—each having a plurality of input ports and one output port, the output ports of the combiners (6)—being connected to the input ports of the central wavelength router—(5),
 - a subset of the ring nodes (4)—of the ring network, each node (4)—of the subset including a tunable transmitter (26)—and a tunable receiver (25)—to communicate optical data packets over the star subnetwork—(3), the tunable transmitters (26)—each being connected to an input port of one of the combiners—(6), wherein
- optical data packets routed between two ring nodes (4)—of the subset over the star subnetwork (3)—are assigned a specific wavelength that determines the routing of the data packets through the central wavelength router—(5).

25. The network according to claim 1~~24~~, wherein the central wavelength router (5)—is a single arrayed waveguide grating.

26. The network according to claim ~~1~~ or 24 or 25, additionally comprising a plurality of wavelength independent splitters (7)—each having one input port and

a plurality of output ports, the input ports of the splitters ~~(7)~~ being connected to the output ports of the central wavelength router ~~(5)~~, the output ports of the splitters ~~(7)~~ each being connected to a tunable receiver ~~(25)~~ of one of the nodes ~~(4)~~ of the subset.

27. The network according to ~~any preceding claim~~ 24, wherein the nodes ~~(4)~~ of the subset are equally distributed among the ring nodes ~~(2)~~.

28. The network according to ~~any preceding claim~~ 24, wherein an optical amplifier ~~(8)~~ is arranged between the output port of a combiner ~~(6)~~ and the corresponding input port of the central wavelength router ~~(5)~~.

29. The network according to ~~any of claims 3 to 5~~ 26, wherein an optical amplifier ~~(8)~~ is arranged between an output port of the central wavelength router ~~(5)~~ and the input port of the corresponding splitter ~~(7)~~.

30. The network according to ~~any preceding claim~~ 24, wherein each node ~~(4)~~ of the subset comprises conversion means ~~(21, 22)~~ for optical to electrical to optical conversion of the signals, and wherein the tunable transmitter ~~(26)~~ and the tunable receiver ~~(25)~~ of a node ~~(4)~~ perform electrical to optical and optical to electrical signal conversion, respectively.

31. The network according to ~~claim 7~~ 30, wherein each node ~~(4)~~ of the subset comprises transit queues ~~(23)~~ and station queues ~~(24)~~, the station queues ~~(24)~~ comprising receive queues ~~(241)~~ and transmit queues ~~(242)~~, one receive queue ~~(241)~~ being connected to the tunable receiver ~~(25)~~ and one transmit queue ~~(242)~~ being connected to the tunable transmitter ~~(26)~~.

32. The network according to any preceding claim 24, further comprising protocol means for routing optical data packets to be sent from a given source ring node ~~(2, A)~~ to a given destination ring node ~~(2, B)~~ over the shortest network path, including routing the data packets over the single channel ring network ~~(1)~~ and over the star subnetwork ~~(3)~~.

33. The network according to any preceding claim 24, additionally comprising:

- means for assigning a wavelength to data packets being sent over the star subnetwork ~~(3)~~ from a given source subset node ~~(4)~~ of the subset to a given destination subset node ~~(4)~~ of the subset, the wavelength determining the route of the data packets through the star subnetwork ~~(3)~~,
- means for tuning the tunable transmitter ~~(26)~~ of the source subset node ~~(4)~~ to the assigned wavelength, and
- means for tuning the tunable receiver ~~(25)~~ of the destination subset node ~~(4)~~ to the assigned wavelength.

34. The network according to claim ~~10~~ 33, wherein the means for assigning a wavelength comprise:

- means for determining the shortest route for data packets being sent from a given source ring node ~~(2, A)~~ to a given destination ring node ~~(2, B)~~,
- means for determining within the shortest route a source subset node ~~(4)~~ and a destination subset node ~~(4)~~ routing the data packets over the star subnetwork ~~(3)~~ in a short-cut,
- means for determining a wavelength to route the data packets from the source subset node ~~(4)~~ to the destination subset node ~~(4)~~.

35. The network according to claim ~~10~~ or ~~11~~ 33, further comprising means for putting the data packets received at the destination subset node ~~(4)~~ on the single channel optical ring network ~~(1)~~ in case the destination subset node ~~(4)~~ is different from the destination node ~~(2, B)~~.

36. The network according to any preceding claim 24, wherein the single channel optical ring network ~~(1)~~ is a bidirectional dual-fiber ring network or a bidirectional single-fiber ring network.

37. The network according to any preceding claim 24, wherein the hybrid optical network is a packet switched metropolitan area network.

38. The network according to any preceding claim 24, wherein a passive star coupler ~~(15)~~ is arranged in parallel with the central wavelength router ~~(5)~~, each node ~~(4)~~ of the subset being coupled both to the central wavelength router ~~(5)~~ and the passive star coupler ~~(15)~~, and with the central wavelength router ~~(5)~~ routing data packets assigned to wavelengths of a first waveband and the passive star coupler ~~(15)~~ routing data packets assigned to wavelengths of a second waveband.

39. A method of routing data packets between a source ring node ~~(2, A)~~ and a destination ring node ~~(2, B)~~ of a hybrid optical network that comprises a peripheral optical ring network ~~(1)~~ with a plurality of ring nodes ~~(2)~~ and a star network ~~(3)~~ with a central wavelength router ~~(5)~~ and a subset of the ring nodes ~~(2)~~, each node ~~(4)~~ of the subset including means ~~(25, 26)~~ to communicate optical data packets over the star subnetwork ~~(3)~~, the method comprising:

- putting data packets to be transmitted on the optical ring network ~~(1)~~ at the source ring node ~~(2, A)~~,

- determining a source subset node ~~(4)~~—and a destination subset node ~~(4)~~—of the subset which are part of a route for data packets being sent from the source ring node ~~(2, A)~~—to the destination ring node ~~(2, B)~~,
5
- pulling incoming source ring node data packets from the optical ring network ~~(1)~~—at the source subset node—~~(4)~~,
- transmitting the pulled data packets over the star subnetwork ~~(3)~~—to the destination subset node—~~(4)~~,
10
- sending the data packets from the destination subset node ~~(4)~~—to the destination ring node ~~(2, B)~~—over the optical ring network ~~(1)~~—if the destination ring node ~~(2, B)~~—is unequal to the destination subset node—~~(4)~~, and
15
- taking the data packets from the optical ring network ~~(1)~~—at the destination ring node—~~(2, B)~~.

40. The method of claim ~~16~~39, wherein the source subset node ~~(4)~~—and the destination subset node ~~(4)~~—are nodes of the shortest route for data packets from the source ring node ~~(2, A)~~—to the destination ring node ~~(2, B)~~—over the hybrid network.
20

41. The method of claim ~~16~~ or ~~17~~39 or 40, wherein the optical ring network ~~(1)~~—is a single channel optical ring network, the optical data packets pulled from the single channel optical ring network ~~(1)~~—being converted in the source subset node ~~(4)~~—to an optical wavelength that allows routing of the data packets to the destination subset node ~~(4)~~—over the star subnetwork ~~(3)~~.
25
30

42. The method of claim ~~18~~41, wherein the optical data signals on the optical ring network ~~(1)~~—are converted to electrical data signals when taken from the ring, and wherein the electrical data signals are converted to
35

optical data signals of a specific wavelength that determines the routing of the data signals across the star subnetwork~~-(3)~~.

- 5 43. The method of claim~~19~~42, wherein the optical data signals are placed in a transmit queue ~~(242)~~ when taken from the optical ring network ~~(1)~~ and transmitted from the transmit queue ~~(242)~~ to a tunable transmitter ~~(26)~~ of the source subset node~~-(4)~~.
- 10 44. The method of claim~~19 or 20~~42, additionally comprising the step of regenerating the signal after conversion to an electrical signal.
- 15 45. The method of ~~any of claims 16 to 21~~ 39, additionally comprising the step of the source subset node ~~(4)~~ transmitting control data with node reservation information to the other nodes ~~(4)~~ of the subset prior to transmitting the data packets over the star
- 20 subnetwork~~-(4)~~.
- 25 46. The method of claim~~22~~45, wherein the node reservation information comprises data about the source address of the source subset node~~-(4)~~, data about the destination address of the destination subset node ~~(4)~~ and data about the length of the corresponding data packet.

SummaryAbstract

~~The invention regards a~~ hybrid optical network comprising a
 single channel optical ring network (1) ~~with a plurality of~~
 5 ring nodes (2) ~~and a star subnetwork (3). The star subnetwork~~
~~(3) comprises a central wavelength router (5), a plurality of~~
~~combiners (6) being connected to input ports of the central~~
~~wavelength router (5), and a subset of the ring nodes (4) of~~
~~the ring network, each node (4) of the subset including a~~
 10 ~~tunable transmitter (26) and a tunable receiver (25) to~~
~~communicate optical data packets over the star subnetwork~~
~~(3). Optical data packets routed between two ring nodes (4)~~
~~of the subset over the star subnetwork (3) are assigned a~~
~~specific wavelength that determines the routing of the data~~
 15 ~~packets through the central wavelength router (5). The~~
~~invention further regards a method of routing data packets~~
~~between a source ring node (2, A) and a destination ring node~~
~~(2, B) of a hybrid optical network. The method includes~~
~~pulling incoming data packets from the optical ring network~~
 20 ~~at a subset node of the star subnetwork which is neither a~~
~~source node nor a destination node, and transmitting the~~
~~pulled data packets over the star subnetwork (3).~~

Figure IG. 1